

COMPUBALLAST®: Best energy saving eBallasts
Universal Voltage 95 to 265V Energy Miser
Electronic Ballasts For 100W MH Lamps.



Our MH CompuBallast® - Saves Energy!

Designed to replace electro-magnetic ballasts with advanced Electronic Ballasts and save energy – 26% plus.
The igniter and capacitor eliminated for extra saving.
Our electronic ballasts incorporate the latest IC technology.

This *CBM90100U* Universal Voltage electronic ballast is designed for MH 100W M90 lamp. Compliant with c(UL)us, c(CSA)us and CE standards.

26% Plus Savings

Reliable Product

CBM90100U

Universal Voltage eBallast for *MH 100W M90 lamp*

How much can you save? $\Sigma(kWh+maintenance+igniter+...)$

MH electronic ballast for 100W, M90 lamp
Universal Input voltages = 95V to 265V at 50/60Hz
Ballast input = 100W; output = 90W
Lamp Current Crest Factor = 1.55
Ballast factor (BF) = 0.99
Aluminum enclosure 0.04"AWG
Enclosure size = 7.8"L x 2.4"W x 1.9"H; Wt=1.2Lb.
Accommodates variations in lamp voltage
Permits re-lamping without damage to lamp or ballast
Minimum starting temperature = -30C

Power Factor > 0.99
THD < 0.05
Energy saving = 26% plus.
(compared with Magnetic)
Type 1 Outdoor - Encapsulated
Extends Lamp Life
Mounting holes = 8.4" apart
No Buzz, No Flicker
Constant Lumen Output

36 Months Limited Replacement Warranty

12/01/2007

we reserve the rights to make changes without prior notice

Established 1976

Call us for price quotation & lead times

COMPUCHARGE INC.

Tel: 514-483-4356 Fax: 514-483-5985 E-Mail: info@compucharge.com