

**COMPUBALLAST®: Best energy saving eBallasts**  
**Universal Voltage 95 to 265V Energy Miser**  
**Electronic Ballasts for 70W MH Lamps.**

---



**Our MH CompuBallast® - Saves Energy!**

Designed to replace electro-magnetic ballasts with advanced Electronic Ballasts and save energy – 33% plus.  
The igniter and capacitor eliminated for extra saving.  
Our electronic ballasts incorporate the latest IC technology.

This CBM9870U Universal Voltage electronic ballast is designed for MH 70W M98 lamp. Compliant with c(UL)us, c(CSA)us and CE standards.

**33% Plus Savings**

**Reliable Product**

# **CBM9870U**

**Universal Voltage eBallast for MH 70W M98 lamp**

---

**How much can you save?  $\Sigma(kWh+maintenance+igniter+...)$**

MH electronic ballast for 70W, M98 lamp  
Universal Input voltages = 95 to 265V at 50/60Hz  
Ballast input = 70W; output = 63W  
Lamp Current Crest Factor = 1.55  
Ballast factor (BF) > 0.99  
Aluminum enclosure 0.04"AWG  
Enclosure size = 7.8"L x 2.4W" x 1.9"H; Wt=1.2Lb.  
Constant Lumen output with variations in line voltage  
Permits relamping without damage to lamp or ballast

Power Factor > 0.99  
THD < 0.05  
Energy saving = 33% plus  
(compared with Magnetic)  
Type 1 Outdoor - Encapsulated  
Extends Lamp Life  
Mounting holes = 8.4" apart  
No Buzz, No Flicker  
Constant Lumen Output

**36 Months Limited Replacement Warranty**

---

12/01/2007

we reserve the rights to make changes without prior notice

Established 1976

Call us for price quotation & lead times

## **COMPUCHARGE INC.**

Tel: 514-483-4356 Fax: 514-483-5985 E-Mail: [info@compucharge.com](mailto:info@compucharge.com)