

COMPUBALLAST®: Best energy saving eBallasts
Dimmable Universal Voltage 100% to 3%
Electronic Ballasts for 70W MH Lamps.



Our MH CompuBallast® - Saves Energy!

This eBallast is designed to dim from 100% to 3% in lumens and 100% to 15% in Watts. It is controlled by 0 to 10Vdc. It delivers energy savings of ...33% to 85% in Watts. Our electronic ballasts incorporate the latest IC technology.

This Dimmable CBM9870UD Universal Voltage electronic ballast is designed for MH 70W M98 lamp. Compliant with c(UL)us, c(CSA)us and CE standards

33% to 65% Savings

Reliable Product

CBM9870UD

Dimmable Universal Voltage eBallast for MH 70W M98 lamp

How much can you save? $\Sigma(kWh+Dimming+maintenance+ \dots)$

Dimmable HPS electronic ballast for 70W ANSI M98
Universal Input voltages = 95 to 265V at 50/60Hz
Ballast input = 70W; output = 63W at 100%
Lamp Output = 100% dimmed to 3% in Lumens
Lamp Current Crest Factor = 1.55
Ballast factor (BF) = 0.99 at 70W
Enclosure size = 8.0"L x 4.0"W x 2.0"H; Wt=2.1Lb.
Constant Lumen output with variations in line voltage
Permits relamping without damage to lamp or ballast

Power Factor > 0.99
THD < 0.05
Energy saving = 33% plus
(extra savings when dimmed)
Type 1 Outdoor - Encapsulated
Extends Lamp Life
Mounting holes = 8.4" apart
No Buzz, No Flicker
Constant Lumen Output

36 Months Limited Replacement Warranty

12/01/2007

we reserve the rights to make changes without prior notice

Established 1976

Call us for price quotation & lead times

COMPUCHARGE INC.

Tel: 514-483-4356 Fax: 514-483-5985 E-Mail: info@compucharge.com